

DIESEL GENERATOR SET

Model: MDS-200T

Rate Power: 182kVA/ 50Hz/ 3 phases

Applications:

Home, Buildings, Hospitals, Train station, Bank, Telecom, Mining, Military, Outdoor projects, etc.

Features and Benefits

- Tightly structure, excellent design and craft
- Excellent cooling system, reliable performance under the harshest conditions (ambient temperature up to 40°C and altitudes up to 1000m)
- Self-diagnostic capability simplifies troubleshooting
- LCD display shows system status setup information



- Automatic voltage regulator protects your sensitive electronics from harmonic distortion and unstable power quality
- Soundproof type: Very quite running: 65±3
- Enclosed muffler for added quietness
- Service and; maintenance accessible through easy-latch side service door

Generator Data

| Prime Power (kVA) | 182 |
|--------------------------------------|----------------|
| Standby Power (kVA) | 200 |
| Rated Frequency (Hz) | 50 |
| Running Noise db(A)/7m (Silent type) | 70±3 |
| Voltage (V) | 230/380 |
| Curent (A) | 277 |
| No.Phase | 3 |
| Silent Type-Dimension (LxWxH) (mm) | 3430x1150x1720 |
| Silent Type-Weight (kg) | 2500 |
| Fuel Tank Capacity (L) | 1 |
| Power factor | 0.8 |





Engine Specifications

Main features:

Brand: Mitsubishi – MHI Japan

- 6-cylinder, water-cooled, in line diesel engine.
- Efficient fuel system for max power output and durability.
- Large-capacity air cleaner.
- Cost effective, fuel efficient and reliable performance.
- Functional engine with compact structure.
- Excellent after-sales service and sufficient spare parts supplying.
- Easy installation and ready access for routine maintenance

| Model | 6D24T | |
|------------------------|---------------------|--|
| Output Power (kw) | 164 | |
| Cylinder No. & Config. | 6, In line | |
| Туре | 4 cycle , Diesel | |
| Displacement (liters) | 11.945 | |
| Governor | Mechanical type | |
| Engine System (r/min) | 1500 | |
| Air intake system | Turbo, Inter-cooled | |
| Fuel Consumption (L/h) | 41 | |
| Oil Capacity (L) | 37 | |
| Compression ratio | 15.1:1 | |
| | | |

Alternator specifications

| Main Features: | Brand options: | Stamford/ Mecc Alte/ Benzen |
|--|-------------------|-----------------------------|
| Advanced automatic voltage regulator (AVR) | | |
| control for trouble-free operation under the | Model | |
| most demanding conditions. | | 100 |
| • 2/3 pitch winding as standard, to avoid | Rated Power (kVA) | 182 |
| excessive neutral current. | Excitation System | Brushless, self-exciting |
| Single or two bearing construction with | | |
| dynamically balanced rotor and sealed-for-life | Connection Type | 3 phases, 4 wires |
| bearings. | | |
| Easy access for installation and maintenance. | Pole No | 4 |
| IP23 as standard. | Pogulator tupo | AVR |
| | Regulator type | AVK |
| Self-excited control system. | Protection class | IP23 |
| Resist of corruption of oil and acid. | | 11 25 |
| | Insulation class | Н |





Options:



Control Panel System



DEEP SEA

DATAKOM



Main Features:

- Using microprocessor as a core, graphics LCD with big screen and backlight, key touch for operation
- All parameters use digital modulation, with higher reliability and stability
- Built-in speed/frequency detecting units can accurately judge the states such as crank success and over speed

Precision measure and display of:

- Generator voltage
- Generator current
- Generator frequency
- Generator active power (kW)
- ✓ Generator inactive power (kW)
- Generator apparent power (kVA)
- Generator power factor
- Generator starts count
- Generator hour count
- Cumulate electric energy (kWh)
- ✓ Generator temperature
- Generator pressure
- Start battery voltage

- Security password-protected programming levels
- Power supply range is wide, accommodating to different starting battery voltage environment
- Built-in watch dog can never be dead halt, ensuring smooth program execution
- Modular configuration design, inserted type connection terminals, flush type installation, compact structure, easy installation

Protection:

- Emergency stop
- High water temperature
- ✓ Low oil pressure
- Over speed
- Under speed
- Loss of speed signal
- Generator over frequency
- Generator under frequency
- Generator over voltage
- Generator under voltage
- Generator over current
- Fail to start
- Auxiliary inputs

* Reserves the right to change the specifications and designs without notice.

