



# DIESELGENERATOR SET

Model: DDS-250T

Rate Power: 225kVA/ 50Hz/ 3 phases

## **Applications:**

Home, Buildings, Hospitals, Train station, Bank, Telecom, Mining, Military, Outdoor projects, etc.

## **Features and Benefits**

- Tightly structure, excellent design and craft
- Excellent cooling system, reliable performance under the harshest conditions (ambient temperature up to 40°C and altitudes up to 1000m)
- Self-diagnostic capability simplifies troubleshooting
- LCD display shows system status setup information

Color choices:



DDS-series

 Automatic voltage regulator protects your sensitive electronics from harmonic distortion and unstable power quality

STREET, STREET

- Soundproof type: Very quite running: 70±2dB(A) at 23ft(7m) at normal load.
- Enclosed muffler for added quietness
- Service and; maintenance accessible through easy-latch side service door

### **Generator Data**

Prime Power (kVA)	225
Standby Power (kVA)	-250
Rated Frequency (Hz)	50
Running Noise db(A)/7m (Silent type)	70±2(dB)A
Vltage (V)	220/380
Curent (A)	418
No.Phase	3
Silent Type-Dimension (LxWxH) (mm)	3600*1500*1800
Silent Type-Weight (kg)	~3500
Fuel Tank Capacity (L)	~200
Fuel	Diesel









# **Engine Specifications**

### Main features:

### **Brand: Doosan**

- An 8-liter engine for an inline, 6-cylinder, turbo/intercooler generator.
- Efficient fuel system for max power output and durability.
- Large-capacity air cleaner.
- Cost effective, fuel efficient and reliable performance.
- Functional engine with compact structure.
- Excellent after-sales service and sufficient spare parts supplying.
- Easy installation and ready access for routine maintenance

Model	DP086LA
Output Power (kw)	201
Cylinder No. & Config.	6, In-line
Туре	Vertical, water-cooled, 4-cycle diesel engine
Displacement (liters)	8.071
Governor	Electric type
Engine System (r/min)	1500
Air intake system	Turbo, Inter-cooled
Fuel Consumption (L/h)	~42
Oil Capacity (L)	16
Compression ratio	8.1

### **Alternator specifications**

#### **Main Features:**

- Advanced automatic voltage regulator (AVR) control for trouble-free operation under the most demanding conditions.
- 2/3 pitch winding as standard, to avoid excessive neutral current.
- Single or two bearing construction with dynamically balanced rotor and sealed-for-life bearings.
- Easy access for installation and maintenance.
- IP23 as standard.
- Self-excited control system.
  Resist of corruption of oil and acid.

Brand options:	Sinocox/Stamford/ Benzen
Model	4-7
Rated Power (kVA)	225
Excitation System	Brushless, self-exciting
Connection Type	3 phases, 4 wires
Pole No	4
Regulator type	AVR
Protection class	IP23
Insulation class	Н









#### **Options:**



### **Control Panel System**



DATAKOM



COMAP

#### **DEEP SEA**

#### Main Features:

- Using microprocessor as a core, graphics LCD with big screen and backlight, key touch for operation
- All parameters use digital modulation, with higher reliability and stability
- Built-in speed/frequency detecting units can accurately judge the states such as crank success and over speed

#### Precision measure and display of:

- Generator voltage
- Generator current
- Generator frequency
- Generator active power (kW)
- Generator inactive power (kW)
- Generator apparent power (kVA)
- Generator power factor
- Generator starts count
- Generator hour count
- Cumulate electric energy (kWh)
- Generator temperature
- Generator pressure
  - Start battery voltage

- Security password-protected programming levels
- Power supply range is wide, accommodating to different starting battery voltage environment
- Built-in watch dog can never be dead halt, ensuring smooth program execution
- Modular configuration design, inserted type connection terminals, flush type installation, compact structure, easy installation

#### **Protection:**

- Emergency stop
- High water temperature
- Low oil pressure
  - Over speed
- Under speed
- Loss of speed signal
- Generator over frequency
- Generator under frequency
- Generator over voltage
- Generator under voltage
- Generator over current
- Fail to start
  - Auxiliary inputs

\* Reserves the right to change the specifications and designs without notice.

