



DIESEL GENERATOR SET

Model: PDS-220T

Rate Power: 200kVA/ 50Hz/ 3 phases

Applications:

Home, Buildings, Hospitals, Train station, Bank, Telecom, Mining, Military, Outdoor projects, etc.

Features and Benefits

- Tightly structure, excellent design and craft
- Excellent cooling system, reliable performance under the harshest conditions (ambient temperature up to 40°C and altitudes up to 1000m)
- Self-diagnostic capability simplifies troubleshooting
- LCD display shows system status setup information



Color choices:



- Automatic voltage regulator protects your sensitive electronics from harmonic distortion and unstable power quality
- Soundproof type: Very quite running: 75±3dB(A) at 23ft(7m) at normal load.
- Enclosed muffler for added quietness
- Service and; maintenance accessible through easy-latch side service door

Generator Data

| Prime Power (kVA) | 200 |
|--------------------------------------|----------------|
| Standby Power (kVA) | 220 |
| Rated Frequency (Hz) | 50 |
| Running Noise db(A)/7m (Silent type) | 75±3 |
| VItage (V) | 220/380 |
| Curent (A) | 303 |
| No.Phase | 3 |
| Silent Type-Dimension (LxWxH) (mm) | 3600*1130*2080 |
| Silent Type-Weight (kg) | 2676 |
| Fuel Tank Capacity (L) | 350 |
| Fuel | Diesel |

PDS-220T Page 1





Engine Specifications

Main features:

Brand: PERKINS

- 6-cylinder, water-cooled, in-line diesel engine.
- Efficient fuel system for max power output and durability.
- · Large-capacity air cleaner.
- Cost effective, fuel efficient and reliable performance.
- Functional engine with compact structure.
- Excellent after-sales service and sufficient spare parts supplying.
- Easy installation and ready access for routine maintenance

| | Model | 1106A-70TAG4 |
|--|----------------------------|---------------------|
| | Output Power (kw) | 196.3 |
| | Cylinder No. & Config. | 6, In-line |
| | Туре | 4 cycle , Diesel |
| | Displacement (liters) | 7.01 |
| | Governor | Elech type |
| | Engine System (r/min) | 1500 |
| | Air intake system | Turbo, Inter-cooled |
| | Fuel Consumption 100% load | 45.8 |
| | Oil Capacity (L) | 21 |
| | Compression ratio | 16:1 |

Alternator specifications

Main Features:

- Advanced automatic voltage regulator (AVR) control for trouble-free operation under the most demanding conditions.
- 2/3 pitch winding as standard, to avoid excessive neutral current.
- Single or two bearing construction with dynamically balanced rotor and sealed-for-life bearings.
- Easy access for installation and maintenance.
- IP23 as standard.
- Self-excited control system.
 Resist of corruption of oil and acid.

| Brand options: | Mecc-Atle/ Leroy Somer/ Benzen |
|-------------------|--------------------------------|
| Model | |
| Rated Power (kVA) | 200 |
| Excitation System | Brushless, self-exciting |
| Connection Type | 3 phases, 4 wires |
| Pole No | 4 |
| Regulator type | AVR |
| Protection class | IP23 |
| Insulation class | н |





Options:



Control Panel System





DEEP SEA DATAKOM COMAP

Main Features:

- Using microprocessor as a core, graphics LCD with big screen and backlight, key touch for operation
- All parameters use digital modulation, with higher reliability and stability
- Built-in speed/frequency detecting units can accurately judge the states such as crank success and over speed

Precision measure and display of:

- Generator voltage
- Generator current
- Generator frequency
- Generator active power (kW)
- Generator inactive power (kW)
- Generator apparent power (kVA)
- Generator power factor
- Generator starts count
- Generator hour count
- Cumulate electric energy (kWh)
- Generator temperature
- Generator pressure
- Start battery voltage

- Security password-protected programming levels
- Power supply range is wide, accommodating to different starting battery voltage environment
- Built-in watch dog can never be dead halt, ensuring smooth program execution
- Modular configuration design, inserted type connection terminals, flush type installation, compact structure, easy installation

Protection:

- Emergency stop
- High water temperature
- Low oil pressure
- Over speed
- ✓ Under speed
- Loss of speed signal
- Generator over frequency
- Generator under frequency
- Generator over voltage
- Generator under voltage
- Generator over current
- Fail to start
- Auxiliary inputs

^{*} Reserves the right to change the specifications and designs without notice.

