

Model BZ3RD-4A/1S


Genset	
Prime Power (kVA)	2.8
Standby Power (kVA)	3
No.Phase	1
Voltage/Frequency	220V - 50Hz
Engine speed (rpm)	3000
Current (A)	12.7
DC output (V)	12V/8.3A
Starting system	Electric
Running Noise (db(A)@7m)	68-72
Silent Type-Dimension (mm)	910x520x725
Fuel Tank (L)	16
Silent Type-Weight (kg)	120
Power factor	1
Certificate	ISO 9001:2015

Engine	
Model	BZ178FA
Origin	China
Brand	Benzen Power
Cylinder No. & Config	1L
Fuel Consumption (L/h)*	0.93
Oil Capacity (L)	1
Displacement (cc)	296
Air intake system	Air-cooled

Alternator	
Brand Alternator	Benzen Power
Rated Power (kVA)	3.3

Model BZ3RD-4A/3S


Genset	
Prime Power (kVA)	3.5
Standby Power (kVA)	3.75
No.Phase	3
Voltage/Frequency	220/380V - 50Hz
Engine speed (rpm)	3000
Current (A)	4.3
DC output (V)	12V/8.3A
Starting system	Electric
Running Noise (db(A)@7m)	68-72
Silent Type-Dimension (mm)	910x520x725
Fuel Tank (L)	16
Silent Type-Weight (kg)	120
Power factor	0.8
Certificate	ISO 9001:2015

Engine	
Model	BZ178FA
Origin	China
Brand	Benzen Power
Cylinder No. & Config	1L
Fuel Consumption (L/h)*	0.93
Oil Capacity (L)	1
Displacement (cc)	296
Air intake system	Air-cooled

Alternator	
Brand Alternator	Benzen Power
Rated Power (kVA)	4.13

Model BZ3RD-6A/1S


Genset	
Prime Power (kVA)	5
Standby Power (kVA)	5.5
No.Phase	1
Voltage/Frequency	220V - 50Hz
Engine speed (rpm)	3000
Current (A)	22.7
DC output (V)	12V/8.3A
Starting system	Electric
Running Noise (db(A)@7m)	68-72
Silent Type-Dimension (mm)	910x520x725
Fuel Tank (L)	16
Silent Type-Weight (kg)	148
Power factor	1
Certificate	ISO 9001:2015

Engine	
Model	BZ186FA
Origin	China
Brand	Benzen Power
Cylinder No. & Config	1L
Fuel Consumption (L/h)*	1.45
Oil Capacity (L)	1.4
Displacement (cc)	418
Air intake system	Air-cooled

Alternator	
Brand Alternator	Benzen Power
Rated Power (kVA)	5.5

Model BZ3RD-6A/3S


Genset	
Prime Power (kVA)	6
Standby Power (kVA)	7
No.Phase	3
Voltage/Frequency	220/380V - 50Hz
Engine speed (rpm)	3000
Current (A)	7.6
DC output (V)	12V/8.3A
Starting system	Electric
Running Noise (db(A)@7m)	68-72
Silent Type-Dimension (mm)	910x520x725
Fuel Tank (L)	16
Silent Type-Weight (kg)	148
Power factor	0.8
Certificate	ISO 9001:2015

Engine	
Model	BZ186FA
Origin	China
Brand	Benzen Power
Cylinder No. & Config	1L
Fuel Consumption (L/h)*	1.45
Oil Capacity (L)	1.4
Displacement (cc)	418
Air intake system	Air-cooled

Alternator	
Brand Alternator	Benzen Power
Rated Power (kVA)	7

Model BZ3RD-8A/1S


Genset	
Prime Power (kVA)	6
Standby Power (kVA)	6.5
No.Phase	1
Voltage/Frequency	220V - 50Hz
Engine speed (rpm)	3000
Current (A)	29.5
DC output (V)	12V/8.3A
Starting system	Electric
Running Noise (db(A)@7m)	68-72
Silent Type-Dimension (mm)	910x520x725
Fuel Tank (L)	16
Silent Type-Weight (kg)	153
Power factor	1
Certificate	ISO 9001:2015

Engine	
Model	BZ192FB
Origin	China
Brand	Benzen Power
Cylinder No. & Config	1L
Fuel Consumption (L/h)*	1.97
Oil Capacity (L)	1.4
Displacement (cc)	498
Air intake system	Air-cooled

Alternator	
Brand Alternator	Benzen Power
Rated Power (kVA)	6.6

Model BZ3RD-8A/3S


Genset	
Prime Power (kVA)	7.5
Standby Power (kVA)	8
No.Phase	3
Voltage/Frequency	220/380V - 50Hz
Engine speed (rpm)	3000
Current (A)	9.9
DC output (V)	12V/8.3A
Starting system	Electric
Running Noise (db(A)@7m)	68-72
Silent Type-Dimension (mm)	910x520x725
Fuel Tank (L)	16
Silent Type-Weight (kg)	153
Power factor	0.8
Certificate	ISO 9001:2015

Engine	
Model	BZ192FB
Origin	China
Brand	Benzen Power
Cylinder No. & Config	1L
Fuel Consumption (L/h)*	1.97
Oil Capacity (L)	1.4
Displacement (cc)	498
Air intake system	Air-cooled

Alternator	
Brand Alternator	Benzen Power
Rated Power (kVA)	8.25

Model BZ3RD-9A/1S


Genset	
Prime Power (kVA)	8
Standby Power (kVA)	8.5
No.Phase	1
Voltage/Frequency	220V - 50Hz
Engine speed (rpm)	3000
Current (A)	36.4
DC output (V)	12V/8.3A
Starting system	Electric
Running Noise (db(A)@7m)	70-73
Silent Type-Dimension (mm)	1013x594x828
Fuel Tank (L)	30
Silent Type-Weight (kg)	212
Power factor	1
Certificate	ISO 9001:2015

Engine	
Model	BZ688FG
Origin	China
Brand	Benzen Power
Cylinder No. & Config	1L
Fuel Consumption (L/h)*	2.6
Oil Capacity (L)	1.85
Displacement (cc)	588
Air intake system	Air-cooled

Alternator	
Brand Alternator	Benzen Power
Rated Power (kVA)	8.5

Model BZ3RD-9A/3S


Genset	
Prime Power (kVA)	10
Standby Power (kVA)	10.6
No.Phase	3
Voltage/Frequency	220/380V - 50Hz
Engine speed (rpm)	3000
Current (A)	12.2
DC output (V)	12V/8.3A
Starting system	Electric
Running Noise (db(A)@7m)	70-73
Silent Type-Dimension (mm)	1013x594x828
Fuel Tank (L)	30
Silent Type-Weight (kg)	212
Power factor	0.8
Certificate	ISO 9001:2015

Engine	
Model	BZ688FG
Origin	China
Brand	Benzen Power
Cylinder No. & Config	1L
Fuel Consumption (L/h)*	2.6
Oil Capacity (L)	1.85
Displacement (cc)	688
Air intake system	Air-cooled

Alternator	
Brand Alternator	Benzen Power
Rated Power (kVA)	10.6

Model BZ3RD-11A/1S


Genset	
Prime Power (kVA)	9.5
Standby Power (kVA)	10
No.Phase	1
Voltage/Frequency	220V - 50Hz
Engine speed (rpm)	3000
Current (A)	45.5
DC output (V)	12V/8.3A
Starting system	Electric
Running Noise (db(A)@7m)	70-73
Silent Type-Dimension (mm)	1043x594x828
Fuel Tank (L)	30
Silent Type-Weight (kg)	225
Power factor	1
Certificate	ISO 9001:2015

Engine	
Model	BZ1105FD
Origin	China
Brand	Benzen Power
Cylinder No. & Config	1L
Fuel Consumption (L/h)*	2.96
Oil Capacity (L)	2.2
Displacement (cc)	761
Air intake system	Air-cooled

Alternator	
Brand Alternator	Benzen Power
Rated Power (kVA)	11

Model BZ3RD-11A/3S


Genset	
Prime Power (kVA)	11.8
Standby Power (kVA)	12.5
No.Phase	3
Voltage/Frequency	220/380V - 50Hz
Engine speed (rpm)	3000
Current (A)	15.2
DC output (V)	12V/8.3A
Starting system	Electric
Running Noise (db(A)@7m)	70-73
Silent Type-Dimension (mm)	1043x594x828
Fuel Tank (L)	30
Silent Type-Weight (kg)	225
Power factor	0.8
Certificate	ISO 9001:2015

Engine	
Model	BZ1105FD
Origin	China
Brand	Benzen Power
Cylinder No. & Config	1L
Fuel Consumption (L/h)*	2.96
Oil Capacity (L)	2.2
Displacement (cc)	761
Air intake system	Air-cooled

Alternator	
Brand Alternator	Benzen Power
Rated Power (kVA)	13.75

Model BZ3RD-14A/1S


Genset	
Prime Power (kVA)	12
Standby Power (kVA)	13.2
No.Phase	1
Voltage/Frequency	220V - 50Hz
Engine speed (rpm)	3000
Current (A)	54.5
DC output (V)	12V/8.3A
Starting system	Electric
Running Noise (db(A)@7m)	70-73
Silent Type-Dimension (mm)	1200x740x860
Fuel Tank (L)	30
Silent Type-Weight (kg)	280
Power factor	1
Certificate	ISO 9001:2015

Engine	
Model	BZ998F
Origin	China
Brand	Benzen Power
Cylinder No. & Config	1L
Fuel Consumption (L/h)*	3.7
Oil Capacity (L)	3
Displacement (cc)	998
Air intake system	Air-cooled

Alternator	
Brand Alternator	Benzen Power
Rated Power (kVA)	13.2

Model BZ3RD-14A/3S


Genset	
Prime Power (kVA)	15
Standby Power (kVA)	16
No.Phase	3
Voltage/Frequency	220/380V - 50Hz
Engine speed (rpm)	3000
Current (A)	18.2
DC output (V)	12V/8.3A
Starting system	Electric
Running Noise (db(A)@7m)	70-73
Silent Type-Dimension (mm)	1200x740x860
Fuel Tank (L)	30
Silent Type-Weight (kg)	280
Power factor	0.8
Certificate	ISO 9001:2015

Engine	
Model	BZ998F
Origin	China
Brand	Benzen Power
Cylinder No. & Config	1L
Fuel Consumption (L/h)*	3.7
Oil Capacity (L)	3
Displacement (cc)	998
Air intake system	Air-cooled

Alternator	
Brand Alternator	Benzen Power
Rated Power (kVA)	16